

# BDR100 DALLAS READER



- \* **Compatible with DS1990A Dallas Chips**
- \* **Communication via One-Wire**
- \* **48 bit code**
- \* **LED indicator for reading**
- \* **Driver identification**
- \* **Deactivation of engine killer**
- \* **ABS enclosure**
- \* **Wall-mount**
- \* **Compatible with MT865 series trackers**
- \* **Digital identification by momentary contact**



## TECHNICAL SPECIFICATIONS

### RESPONSE TIME

2s

### ENCLOSURE

ABS wall-mount

### PROCESSOR CORE

ARM9

Memory: 1Mb RAM, 1Mb Flash

### ELECTRICAL CHARACTERISTICS

Power: +3.7VDC

### INDICATOR

LED

### INTERFACE

One Wire

### TEMPERATURE RANGE

Operating: -20°C to +60°C

### PHYSICAL CHARACTERISTICS

Dimensions (LxWxH): 102.7 x 48.2 x 22mm

Weight: 30g

### COMPATIBILITY

MT865 series trackers



**BIOSTURK.COM**